



INVERTER PRO 2000 C5



INVERTER PRO 2000 C5

PORTABLE POWER

GENERATING SET Range PRESTIGE

PRODUCT ADVANTAGES

Ergonomic, light and compact equipment
Very Silent
12 V output
Quality current
Low consumption

INVERTER TECHNOLOGY This new, very high performance technology guarantees the stability of the voltage and frequency of your genset to within $\pm 1\%$ of the nominal value. Such high precision makes it possible to produce high-quality current and supply the most demanding equipment.

12V OUTPUT Supplies equipment operating off 12V and in particular for recharging batteries. Connection cables are included.

Range PRESTIGE

Top of the range equipment that is efficient and with low noise emissions, for a wide range of standard requirements.



GENERAL SPECIFICATIONS

Range	PRESTIGE
Frequency (Hz)	50 Hz
Max power (kW)	1,8
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	4,2
75% cons. (l/h)	0,9
75% Autonomy (h)	4,7
Sound power level guaranteed LwA dB(A)	89
Acoustic pressure level @1m in dB(A)	75
Acoustic pressure level @7m in dB(A)	60

ENGINE SPECIFICATIONS

Engine brand	YAMAHA
Engine ref.	MZ80_C5
Engine Type	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm3)	79
Oil system capacity including filters (l)	0,4

ALTERNATOR SPECIFICATION

Technology	Inverter
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

1 socket 230V 10/16A - circuit breaker + 1 socket 12V 8A - circuit breaker+ indicator

DIMENSIONS AND WEIGHT

Length (cm)	49
Width (cm)	28
Height (cm)	44,5
Dry Weight (kg)	21

PACKAGING

Packaging type	Box
Length (cm)	55,5
Width (cm)	36,5
Height (cm)	49,5
Weight (kg)	22
Pallet type	
Number of box by pallet	6
Pallet height (cm)	53
weight of the packaged Pallet (kg)	150



INVERTER PRO 2000 C5

ACCESSORIES SUPPLIED

Spark plug spanner
User and maintenance manual

OPTIONS

R05M	R05M - Manual source inverter for connecting a single-phase generator to a house
3499231001790	RYS2 - Maintenance kit INVERTER PRO 2000 including oil, spark plug and air filter
RPM	RPM - Plug kit for all models: 2 x 16A /230V sockets, 1 x CEE17 16A/230V socket, 1 x 32A/230V socket, 1 x 16A/400V socket
RPQ	RPQ - 1m earth spike, supplied with 2m 10mm ² mains cable
RKD1	RKD1 - Kit of 2 removable differential adaptors for domestic sockets 16A
3499231000922	RCC - Coupling cable for connecting 2 generators for INVERTER PRO 2000