



## HXC 7500 T C5

PORTABLE POWER

GENERATING SET Range INTENS

### PRODUCT ADVANTAGES

Generating set guaranteed 3 years  
HONDA Professional Engine  
Solid and high-performance equipment

STAGE V (2016/1628 EU) : This product is compliant with regulation for implementing requirements relating to gaseous and pollutant emission limits in Europe

### Range INTENS

Equipment that is robust, long-lasting and simple to use for repetitive operations in difficult conditions.



## HXC 7500 T C5

### GENERAL SPECIFICATIONS

Range	INTENS
Frequency (Hz)	50 Hz
Max power (kW)	5,7
Max power (kVA)	7,1
Nominal voltage (V)	400
Number of Phase	Three phase
Fuel	Petrol
Tank (L)	6,1
75% cons. (l/h)	2,5
75% Autonomy (h)	2,4
Sound power level guaranteed LwA dB(A)	100
Acoustic pressure level @1m in dB(A)	86
Acoustic pressure level @7m in dB(A)	72

### ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine ref.	GX390_C5
Engine Type	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm3)	389
Oil system capacity including filters (l)	1,1

### ALTERNATOR SPECIFICATION

Technology	Collar and brush
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

### PLUGS AND PANEL DESCRIPTIVE

1 230V 10/16A socket - circuit breaker + 1 400V 16A socket - circuit breaker

### DIMENSIONS AND WEIGHT

Length (cm)	71,5
Width (cm)	57
Height (cm)	59
Dry Weight (kg)	76

### PACKAGING

Packaging type	Box
Length (cm)	73
Width (cm)	58
Height (cm)	59,5
Weight (kg)	78,5
Pallet type	120/80
Number of box by pallet	6
Pallet height (cm)	192
weight of the packaged Pallet (kg)	481



## HXC 7500 T C5

### ACCESSORIES SUPPLIED

Funnel  
User and maintenance manual

### OPTIONS

- R03** This set includes the hour meter and the differential circuit breaker
- 3499231004012** VERSO 10 T 40A - Manual source inverter for connecting a three-phase generator to a house
- RKB2** RKB2 - Trolley kit for HX 4000 - 6000 – 7500T / HXC 4000 - 6000 – 7500T / TECHNIC 10000 -15000 / VX 200/4 -220-7,5 / WELDARC 300 / TRASH ; Puncture-proof wheels Ø 290 mm
- RH1** RH1 - Protective cover for HX 4000 – 6000 – 7500T / HXC 4000 – 6000 – 7500T / PERFORM 4500 – 4500 XL – 5500T – 5500 T XL – 6500 – 6500 XL – 7500 T – 7500 XL / TECHNIC 6500 – 7500 TE / DIESEL / TRASH ; Dimensions : 82 x 58 x 50 cm
- RPM** RPM - Plug kit for all models: 2 x 16A /230V sockets, 1 x CEE17 16A/230V socket, 1 x 32A/230V socket, 1 x 16A/400V socket
- RPQ** RPQ - 1m earth spike, supplied with 2m 10mm<sup>2</sup> mains cable
- 3499231920831** GSC - Generator Smart Care : Bluetooth box which can be used on all portable generator